# HP LaserJet 1020 Printer





HP LaserJet 1020 Printer

The HP LaserJet 1020 Printer, an excellent laser printer for the cost-conscious user, delivers high-quality LaserJet printing in a compact size, and at a price you can afford.

The space-conscious, value-minded user in a micro or small-business, or working from home, who is faced with many tasks and requires a reliable printing solution for professional-quality documents.

Produce impressive documents with outstanding print quality at an affordable price.


- A low purchase price makes this a great choice for anyone on a budget.
- It includes a high value HP LaserJet print cartridge enabling you to produce professional quality documents economically.
- Get crisp, sharp results from the first page to the last with 1200-dpi effective output quality (600 x 600 dpi resolution) using HP FastRes and REt technology.
- · Achieve precise details, clear text and smooth greyscales with HP's advanced toner formulation and print cartridge technology.

## Get great results from a small package.

- HP's smallest LaserJet its compact size fits easily on a desk, shelf or other convenient space.
- Print your documents quickly with fast speeds of 14 ppm (A4).
- Waste no time as HP's Instant-on Technology delivers the first page of your print job in just ten seconds from warm or cold start.
- Includes 2 MB RAM, and with a duty cycle of 5,000 pages per month large print jobs are no problem.
- Features a single-sheet multipurpose slot for special media and 150 sheet adjustable main tray.

#### The HP LaserJet 1020 Printer is amazingly easy to install, use and maintain.

- Get going with no fuss or delay as the set-up and installation process is straightforward.
- One-door access to the easy-to-install, full-value HP LaserJet print cartridge means installation and replacement are both simple and convenient.
- Hi-Speed USB 2.0 port for fast data transfer.
- The printer has a simple user-friendly interface and you can check status and change configuration with eToolbox.
- Compatible with Windows® 98 SE, Me, 2000 and XP 32-bit.





### **Technical specifications**

recillical specificand	2112				
Print technology	Monochrome laser				
Print speed	Up to 14 ppm First page out: Less than 10 sec. due to Instant-on Technology (no warm-up time – from warm or cold start) Speed specification per industry standard testing methods				
Processor	234 MHz RISC processor				
Memory	2 MB				
Print quality	1200 dpi-like quality (600 dpi with REt and FastRes)				
Print languages	Host-based printing driver				
Economical printing levels	Economode (saves up to 50% toner at 600 dpi), immediate return to Powersave mode after each print job due to Instant-on Technology (saves electricity), N-up printing and manual two-sided printing - duplex (saves paper)				
Duty cycle	Up to 5,000 pages per month				
Print margins (mm)	Top: 4 mm; left: 4 mm; right: 4 mm; bottom: 4 mm				
Media handling	<b>Input</b> Main tray	Capacity Up to 150 sheets	<b>Weight</b> 60 g/m² to 163 g/m²	<b>Size</b> A4, A5, A6, B5, envelopes (C5, DL, B5), postcards 76 x 127 mm to 216 x 356 mm	
	Priority tray	1 sheet	60 g/m² to 163 g/m²	A4, A5, A6, B5, envelopes (C5, DL, B5), postcards 76 x 127 mm to 216 x 356 mm	
	Output: Sheets: up to 100, envelopes: 15, transparencies: 100  Duplex printing: Manual (driver support provided)				
Media types	Plain paper, envelopes, transparencies, cardstock, postcards, labels				
Interface and connectivity	Standard: 1 Hi-Speed USB (compatible with USB 2.0 specifications) port				
Operating systems compatibility	Microsoft® Windows® 98 SE, Me, 2000, XP 32-bit				
Minimum system requirements	Microsoft <sup>®</sup> Windows <sup>®</sup> 98 SE, Me, 2000 or XP, 90 MHz Pentium <sup>®</sup> , 120 MB free hard disk space (10 MB minimum install), CD-ROM drive, USB port (compatible with USB 2.0 specifications)				
Standard software	HP printer software on CD-ROM includes HP installer/uninstaller, host-based driver, HP toolbox for diagnostic status and configuration, help, documentation  Driver downloadable: Latest drivers available from the HP support website at http://www.hp.com/support				
Control panel	2 LED lights (Attention, Ready)				
Power	Requirements: Input voltage 110 to 127 VAC (± 10%), 50/60 Hz (± 2 Hz), 3.5 amps; 220 to 240 VAC (± 10%), 50/60 Hz (± 2 Hz), 2 amps Supply type: Internal Consumption*: Active: 250 watts; Off: 0 watts; Powersave: 2 watts; Standby: 2 watts *Power requirements are based on the country/region where the printer is sold. Do not convert operating voltages. Doing so might damage the printer an void the product warranty.				
Dimensions (w x d x h)	Out of package: 370 x 230 x 208 mm; packaged: 500 x 300 x 345 mm				
Weight	Out of packag	Out of package: 5 kg; packaged: 7.21 kg			
Printer management	HP Toolbox				
Operating environment	Environmental ranges: Operating temperature: 10 to 32.5° C, operating humidity: 20 to 80% RH, recommended operating humidity: 20 to 80% RH, recommended operating temperature: 10 to 32.5° C, storage temperature: 0 to 40° C, storage humidity: 10 to 80% RH. Noise level per ISO 9296: sound power LwAd: 6.2 B(A), Sound pressure: LpAm: 4.9 B(A)				
Certifications	CISPR 22: 1997/EN 55022: 1998 Class B, EN 61000-3-2: 2000, EN 61000-3-3: 1995+A1, EN 55024: 1998+A1, FCC Title 47 CFR, Part 15 Class B (USA), ICES-003, Issue 4, (Canada), GB9254-1998, EMC Directive 89/336/EEC with CE Marking (Europe), other EMC approvals as required by individual countries.  Regulatory standards: IEC 60950-1 (International), EN 60950-1 (EU), IEC 60825-1+A1+A2, UL/cUL Listed (US/Canada), GS License (Europe), EN 60825-1+A11+A2 Class 1, 21 CFR Ch 1/SubCh J (Class 1 Laser/LED Device) GB4943-2001, Low Voltage Directive 73/23/EEC with CE Marking (Europe); other safety approvals as required by individual countries. Energy Star®				

## **Ordering information**

**Q5911A** HP LaserJet 1020 Printer, HP LaserJet print cartridge, getting started guide, printer documentation and software on CD-ROM, power cord

	Accessories
C6518A	HP USB Cable, 2m
	Supplies
Q2612A	HP LaserJet Ultraprecise Print Cartridge, black

Service & support

HP Care Pack, return to

 U6489A/E
 HP Care Pack, return to HP, 3 years

 U8045PA/PE
 HP Care Pack, post

warranty, return to HP, 1 year

H3110A/E Installation and Network
Configuration

http://www.hp.com

Warranty

For more information, please call your local HP sales office or representative: Austria: 0800 242 242, Algeria: (0)61 56 45 43, Bahrain: 800 728, Belgium: (078) 15 20 30 (0.0496€/min), Bulgaria: (+359) 2960 1940, Croatia: (+385 1) 60 60 200, Czech republia: (00 420) 261 108 108 (Prague), Denmark: +45 4812 1000, Egypt: 532 5222, Estonia: (+372) 6813 823, Finland: (+358) 0205 350, France: 0 826 800 400, Germany: 0180 5 665 775 (Business Products) and 0180 5 652 180 (Consumer Products) (12 Cent/min − fixed network), Greece: (01) 678 96 00, Hungary: (+36) 1 382·1111, Iceland: (354) 570 1000, Ireland: +353 1 6158200, Israel: (972) 9-830 4848, Italy: (02) 92121, Kazakhstan: +7 (3272) 980 824, Latvia: 800 80 12, Lithuania: 8 800 10000 or +370 5 2103333, Luxembourg: (+352) 263 160 34, Middle East: 00971 4 883 4427, Morocco (African Region): +212 22 40 47 47, Netherlands: (020) 5476666, Norway: +47 08800, Poland: infolinia 0-800 122 622, Portugal: 808 200 6018, Romania: (+401) 205 3300, Russia: +7 (095) 797 35 00, Saudi Arabia: 800 124 4646, Serbia/Montenegro: +381 11 201 99 00, Slovakia: +421:250222111, Slovenia: +3861 2307 420, South Africa: 0800 118 883, Spain: (91) 634 88 00, Sweden: (08) 444 2000, Switzerland: 0848 88 44 66, Tunisia: 71 891 222, Turkey: +90 (212) 444 71 71, UAE: 8004910, UK: 08705 474747, Ukraine: +380 44 90 61 20.









One-year limited warranty

